

AES-805T

AES/EBU Snake, DB25 to 4 XLR3M and 4 XLR3F, Tascam Pinout

- | | |
|----|---------------------|
| 1 | Channel 7/8 Out (+) |
| 2 | SG (Signal Ground) |
| 3 | Channel 5/6 Out (-) |
| 4 | Channel 3/4 Out (+) |
| 5 | SG |
| 6 | Channel 1/2 Out (-) |
| 7 | Channel 7/8 In (+) |
| 8 | SG |
| 9 | Channel 5/6 In (-) |
| 10 | Channel 3/4 In (+) |
| 11 | SG |
| 12 | Channel 1/2 In (-) |
| 13 | Not Used |
| 14 | Channel 7/8 Out (-) |
| 15 | Channel 5/6 Out (+) |
| 16 | SG |
| 17 | Channel 3/4 Out (-) |
| 18 | Channel 1/2 Out (+) |
| 19 | SG |
| 20 | Channel 7/8 In (-) |
| 21 | Channel 5/6 In (+) |
| 22 | SG |
| 23 | Channel 3/4 In (-) |
| 24 | Channel 1/2 In (+) |
| 25 | SG |



XLR connectors are:

Pin-1 Ground
Pin-2 (+)
Pin-3 (-)

AES-805T



Hosa Technology

HOSA TECHNOLOGY, 6650 CABALLERO BLVD., BUENA PARK, CA 90620
PHONE: 714.522.8878 FAX: 714.522.4540